

## Tender text

### R-4TBM/5

#### UHF PLL pocket transmitter

- Suitable for combination with a headband microphone or an instrument microphone with 4-pole mini XLR connector
- Bandwidth: 36 MHz
- 6 groups, each with up to 22 compatible preset channels
- 1,441 selectable individual frequencies
- REMOSET technology for receiver/transmitter synchronisation
- Adjustable sensitivity ( $\pm 15$  dB)
- Lock function
- 6-level display for indicating battery status and low battery alert, backlit LCD
- Switchable transmitting power

#### There are restrictions or requirements within the EU!

Please read the notes regarding wireless systems in the section "IMPORTANT INFORMATION"!

Specifications:

#### General information

|                            |                                  |
|----------------------------|----------------------------------|
| Description                | pocket transmitter               |
| Carrier frequency range    | 506-542 MHz                      |
| Audio frequency range      | 50-18,000 Hz                     |
| Channels                   | 1                                |
| Operating time             | > 20 h                           |
| Admiss. ambient temp.      | 0-40 °C                          |
| Specifications transmitter |                                  |
| Transmitting power         | 10/50 mW                         |
| Operating range            | 120 m                            |
| Power supply transmitter   | 2 x batt. AA size (not supplied) |
| Width transmitter          | 62 mm                            |
| Height transmitter         | 80 mm                            |
| Depth transmitter          | 23 mm                            |
| Weight transmitter         | 95 g                             |
| Connections transmitter    | 4-pole mini XLR                  |

Brand: JTS

Type: R-4TBM/5

Quantity: 1

Packing dimensions (W x H x L): 0.1 x 0.08 x 0.3 m

Gross weight: 0.36 kg

Net weight: 0.115 kg

Item weight (w/o accessories): 0.095 kg